

## Trove2AG2 Kit / TAG2 Backplane Access & Power Integration Solution

### Description

Altronix Trove™ enclosures and backplanes let you easily integrate Altronix power with AMAG M4000 access controllers and accessories. Trove simplifies board layout and wire management, reduces installation time and labor costs.

### Trove2 Enclosure + TAG2 Backplane Features

- Accommodates AMAG M4000 controllers with or without Altronix power/accessories:
  - Altronix Power Supplies:
    - Up to two (2) eFlow4NB, eFlow6NB, eFlow102NB, eFlow104NB or PoE201.
  - Altronix PoE Switch:
    - One (1) NetWaySP4B.
  - Altronix Sub-Assemblies:
    - Up to three (3) LINQ8PD(CB), ACM8(CB), ACMS8(CB), ACM4(CB), MOM5, PD4UL(CB), PD8UL(CB), PDS8(CB), or VR6
- Includes Altronix Trove2 Enclosure and one (1) removable TAG2 backplane.

### Agency Listings

CE European Conformity

### Features

- Simplifies board layout and wire management
- Convenient knockout configuration:
  - Single 2" diameter knockout located top center of enclosure
  - Sixteen (16) double knockouts (1" and 0.75")
- Accommodates up to four (4) 12VDC/7AH batteries
- 16 AWG powder coated steel
- Includes cam lock, tamper switch and mounting hardware

### Dimensions (H x W x D):

27.25" x 21.5" x 6.5" (692.2mm x 546.1mm x 165.1mm)

### Weights:

Product - 37.1 lbs. (16.83 kg)  
Shipping - 40.85 lbs. (18.53 kg)

### TAG2 Backplane Features

- Accommodates AMAG M4000 controllers with or without Altronix power/accessories:
  - Altronix Power Supplies:
    - Up to two (2) eFlow4NB, eFlow6NB, eFlow102NB, eFlow104NB or PoE201.
  - Altronix PoE Switch:
    - One (1) NetWaySP4B.
  - Altronix Sub-Assemblies:
    - Up to three (3) LINQ8PD(CB), ACM8(CB), ACMS8(CB), ACM4(CB), MOM5, PD4UL(CB), PD8UL(CB), PDS8(CB), or VR6
- Backplane features:
  - Simplifies board layout and wire management
  - 16 AWG galvanized steel

Dimensions: 25.375"H x 19.375"W x 0.3125"D  
(644.5mm x 492.1mm x 8mm)

Weights: Product - 8.0 lbs. (3.63 kg)  
Shipping - 10.0 lbs. (4.53 kg)



Trove2AG2

\* Boards not included



